ELCO Lighting

Dimmer Compatibility Chart

6" LED Inserts

For EL610/611/612/670, EL615/617/627/655, EL621/625 Series

For Reference Only

Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards. Consult the dimmer manufacturer prior to installation to ensure compatibility.

Manufacturer	Product	Part Number	Dimmed Light Output Range
120V Only			
Leviton	Decora IllumaTech® Single Pole/3-Way Preset Dimmer	IPI06	10% - 100%
	Decora Single Pole/3-Way Rocker Slide Dimmer	DSL06-1LZ	10% - 100%
	Decora SureSlide® Single Pole/3-Way with Preset On/Off Switch	6674	5% - 90%
Lutron	Vive 150W LED/CFL, Single Pole, 3-Way Operation, Commercial Application	MRF2S-6ELV	9% - 100%
	HomeWorks® QS for CFL/LED loads, 120V, FP, Commercial/Residential Application	LQSE-4A1-D/MQSE-4A1-D/ MQSE-3A1/MQSE-2A1-D	8% - 100%
	HomeWorks® QS for CFL/LED loads, 120V, RP, Commercial/Residential Application	LQSE-4A1-D/MQSE-4A1-D/ MQSE-3A1/MQSE-2A1-D	7% - 100%
	Energi Savr Node LED+ Phase Adaptive for LED loads, RP, (Zone 1) (Zones 2-4)	QSN-4A5-S	7% - 100%
	Energi Savr Node LED+ Phase Adaptive for LED loads, FP, (Zone 1) (Zones 2-4)	QSN-4A5-S	8% - 100%
	RadioRA 2 600W Incandescent/Halogen loads, Residential Application, RP	RRD-6NA	9% - 100%
	RadioRA 2 250W LED/CFL, 500W Incandescent/Halogen loads, Residential Application, RP	RRD-PRO	9% - 100%
	HomeWorks® QS 150W LED, 600W Incandescent/Halogen loads, Residential Application, RP	HQRD-6NA	9% - 100%
	HomeWorks® QS 250W LED/CFL, 500W Incandescent/Halogen loads, Residential Application, RP	HQRX-PRO	9% - 100%
	HomeWorks® for LED/Incandescent/Halogen loads, RP, (Zone 1) (Zones 2-4)	LQSE-4A5-120-D	7% - 100%
	HomeWorks® for LED/Incandescent/Halogen loads, FP, (Zone 1) (Zones 2-4)	LQSE-4A5-120-D	8% - 100%
	Ariadni®/Toggler® Series 150W Single Pole/3-Way Dimmer	TGCL-153P	5% - 86%
	Maestro® Series 150W Single Pole/3-Way/Multi-Location Dimmer	MACL-153M	5% - 80%
	Skylark Contour® CL Single Pole/3-Way Dimmer	CTCL-153P	10% - 100%
	Caseta Wireless Dimmer	PD-6WCL	10% - 100%

*NOTE: Refer to dimmer manufacturer's documentation for installation instructions and circuit details

Disclaimer: Minimum and maximum loads for LEDs and CFLs are given in number of lamps and may vary depending on the lamp being used. Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards.

Integrating our lighting with your Smart Home System is a breeze. Simply check your Smart Home system for compatible smart switches and cross refrence that with our Dimming Compatibility Chart. Once the switches are integrated with your Smart Home system your lights will be ready to go.

amazon alexa | Google Assistant | Apple HomeKit | INSTEON | LUTRON | wemo

2042 E. Vernon Ave. Vernon CA 90058 Tel 323.231.2600 Fax 323.231.3200 elcolighting.com